INSTALLATION INSTRUCTIONS
LED Pendant
PD-6548

MODERN FORMS

CAUTION: To prevent electrical shock, ensure electricity has been turned off at the circuit breaker before beginning.
- Read all instructions before installing.
- System is intended for installation by a licensed electrician in accordance with the National Electrical Code (NEC) and local regulations.
- When handling the fixture, do not apply pressure to the LEDs. Hold the fixture by the base only.
- Retain installation instructions for future maintenance reference.

WARNING: All parts must be used as indicated in these instructions. This product is designed for use only with the supplied parts and/or accessories designated for use by Modern Forms. Substitution of parts or accessories not designated for use with this product by Modern Forms could result in personal injury or property damage, and will void the warranty. Contact an authorized dealer or the manufacturer if any parts are damaged or missing.


MAINTENANCE NOTE: Coastal conditions may cause mineral and residue build-up on the fixture. We recommend that customers in coastal areas clean all external surfaces of the fixture once every two weeks with a wet cloth.

MISE EN GARDE: Pour éviter tout choc électrique, assurez-vous que le disjoncteur soit mis hors tension avant de commencer.
- Lisez toutes les instructions avant l'installation.
- Le système doit être installé par un électricien licensié conformément au code national de l'électricité (NEC), et également aux règlements locaux.
- Lors de la manipulation du luminaire, n'appuyez pas sur les LED. Tenez-le uniquement par la base.

ATTENTION: Toutes les pièces doivent être utilisées comme indiqué dans ces instructions. Ce produit est conçu pour être utilisé seulement avec les pièces et/ou accessoires fournis pour être utilisés avec les produits Modern Forms. Remplacer des pièces ou accessoires non conçus pour ce produit Modern Forms pourrait causer des dommages corporels ou matériels et pourrait également causer l'annulation de la garantie. Veuillez contacter un revendeur autorisé ou le fabricant si des pièces manquent ou sont endommagées.

NOTE D'ENTRETIEN: Les conditions côtières peut causer une accumulation de minéraux et de résidue sur le luminaire. Nous recommendons aux clients qui resident dans les zones côtières de nettoyer toutes les surfaces externes du luminaire une fois toutes les deux semaines avec un chiffon humide.

HARDWARE



A	B	C	D	E
Wire Connector Qty: 3pcs+1 Extra	Wire Connector Qty: 3pcs+1 Extra	Mounting Screw Qty: 1 Extra	Anchor Screw Qty: 2pcs+1 Extra	Plastic Anchor Qty: 2pcs+1 Extra

modernforms.com
Phone (800) 526.2588
Fax (800) 526.2585

Headquarters/Eastern Distribution Center
44 Harbor Park Drive
Port Washington, NY 11050

Central Distribution Center
1600 Distribution Ct
Lithia Springs, GA 30122

Western Distribution Center
1750 Archibald Avenue
Ontario, CA 91760

Modern Forms retains the right to modify the design of our products at any time as part of the company's continuous improvement program. Jan. 2025

FIG. 1




Fig. 2 Wiring



Fixture Wires Black or Smooth	**House Wires** Black (Live)
Fixture Wires White or Ribbed	**House Wires** White (Neutral)
Fixture Wires Bare wire (Ground)	**House Wires** Green or Bare Copper (Ground)

Fig.3 Switch





Fig.5



modernforms.com
Phone (800) 526.2588
Fax (800) 526.2585

Headquarters/Eastern Distribution Center
44 Harbor Park Drive
Port Washington, NY 11050

Central Distribution Center
1600 Distribution Ct
Lithia Springs, GA 30122

Western Distribution Center
1750 Archibald Avenue
Ontario, CA 91760

INSTALLATION INSTRUCTIONS
LED Pendant
PD-6548

MODERN FORMS

PREPARATION

1. Shut off the power at the circuit breaker and remove existing fixture, including the crossbar.
2. Carefully unpack your new fixture and lay out all the parts in a clear area. Be careful not to lose any small parts necessary for installation.

MOUNTING THE FIXTURE (Fig.1、 Fig.3)

3. Remove the mounting screw (C) and back plate from the fixture.
4. The lamp can switch between four color temperatures (27000K-3000K-3500K-4000K), which can be adjusted to your preference with the switch in the fixture (Fig.3).

   Note: (i) The switch comes with a detachable switch cover, remove the switch cover prior to adjusting the color reattach the switch cover after adjustment is made.

   (ii) Fixture must be powered off to adjust the CCT setting, after each CCT adjustment cycle power on, off then on to show new CCT setting.
5. Drill holes in the wall aligned with the key holes located on the backplate, insert the plastic anchor(E). Secure mounting back plate to the junction box using standard junction box screws that comes with the junction box, fasten it to the wall using wood screw (D).

   Note : (i) Using any other non-original-manufacturer provided junction box screw may result in safety issue;

   (ii) The side of the mounting plate marked "GND" must face out.

   (iii) One screw of the mounting plate must be facing down.
6. Remove mounting nuts and universal joint, select the number of rods that suits you, thread the wires through the rods and gimbales, and finally secure the gimbales to the fixture canopy in the original way.
7. Hook the safety rope properly secured to the bracket on the installed rear plate so that the fixture can be temporarily suspended in place.


CONNECTING THE WIRES (Fig.2、 Fig.4)

8. Connect the driver's output wires , fixture's wires and 4CCTswitch 's wires together using wire connectors (B) as shown in Fig .4.
9. Connect the Driver input wires to junction box as shown in Fig .2. Making sure that all wire connectors (A) are secured. If your outlet box has a green or bare copper ground wire, connect the fixture's ground wire to it. Otherwise, connect the fixture's ground wire directly to the back plate using the GND screw provided. After wires are connected, tuck them carefully inside the junction box.


COMPLETING THE INSTALLATION (Fig. 5)

10. Secure the fixture to the ceiling plate using the canopy screw (C).
11. For slope ceiling applications, rotate swivel at the top of the stem to ensure luminaire is aiming down (Fig.5).
12. As shown in Fig.1, the six luminaires can rotate a certain angle, the maximum Angle is 180°, you can rotate the luminaires according to your use requirements to obtain the best lighting effect.

Fig. 4 Wiring



Back Plate Dimensions



modernforms.com
Phone (800) 526.2588
Fax (800) 526.2585

Headquarters/Eastern Distribution Center
44 Harbor Park Drive
Port Washington, NY 11050

Central Distribution Center
1600 Distribution Ct
Lithia Springs, GA 30122

Western Distribution Center
1750 Archibald Avenue
Ontario, CA 91760